

ASW05kH /06kH /08kH /10kH /12kH -T2-DG ASW08kH /10kH /12kH /15kH-T3-DG

Three phase hybrid inverter

Quick Installation Guide

General Information

This quick installation guide does not replace the description in the user manual.

The contents of this guide may be updated or revised due to product development. The information in this guide is subject to change without notice. The latest version of this document and the manual for installation, commissioning, configuration and decommissioning are to be found in PDF format at www.solplanet.net.

2 Safety

2.1 Intended use

The product is a transformerless hybrid inverter with 2 or 3 MPP trackers and a battery connection that feeds the direct current of the PV array into the connected battery or converts it to grid-compliant three-phase current and then feeds it into the utility grid.

It has a diesel generator interface and supports generator input energy to supply load.

The product also can convert the direct current supplied by the battery into grid-compliant three-phase current. The product has a backup function that can continue to supply selected circuits with power from the battery or PV system in the event of a grid fault.

The product is intended for indoor and outdoor applications.

The product must only be connected with PV modules of protection class II (in accordance with IEC 61730, application class A).

The product is not equipped with an integrated transformer and therefore has no galvanic isolation. The product must not be operated with PV modules which require functional grounding of either the positive or negative PV conductors.

This can cause the product to be irreparably damaged. The product may be operated with PV modules with frames that require protective earthing.

All components must remain within their permitted operating ranges and their installation requirements at all times.

Use the product only in accordance with the information provided in the user manual

and with the locally applicable standards and directives. The three AC terminals (GEN,Load,Grid) are distinguished by color, pay attention to distinguish the terminal color when using, and must be connected according to the terminal color requirements. Any other application may cause personal injury or damage to property.

The product must only be operated in connection with an intrinsically safe lithium-ion battery approved by Solplanet.

The entire battery voltage range must be completely within the permissible input voltage range of the product.

The product must only be used in countries for which it is approved by Solplanet and the grid operator.

The type label must be permanently attached to the product and must be in a legible condition.

This document does not replace any regional, state, provincial, federal or national laws, regulations or standards that apply to the installation, electrical safety and use of the product.

2.2 Important safety instructions

The product has been designed and tested strictly according to the international safety requirements. As with all electrical or electronical devices, there are residual risks despite careful construction. To prevent personal injury and property damage and to ensure long-term operation of the product, read this section carefully and observe all safety information at all times.



Danger to life due to high voltages of the PV array or the battery!

The DC cables connected to the battery, or the PV array may be live. Touching the DC conductors or the live components can cause to lethal electric shocks. If you disconnect the DC connectors from the product under load, an electric arc may occur leading to electric shock and burns.

- Do not touch non-insulated cable ends.
- Do not touch the DC conductors.
- Do not touch any live components of the product.
- Do not open the product.
- Observe all safety information of the battery manufacturer.
- All work on the product must only be carried out by qualified personnel who have read and fully understood all safety information contained in this document and the user manual.
- Disconnect the product from all voltage and energy sources and ensure it cannot be reconnected before working on the product.
- Wear suitable personal protective equipment for all work on the product.



♠ DANGER

Danger to life due to electric shock when touching live components in backup mode!

Even if the AC breaker and the PV switch of the inverter are disconnected, the parts of the system may still be live when the battery is switched on due to backup mode.

- Do not open the product.
- Disconnect the product from all voltage and energy sources and ensure it can not be reconnected before working on the product.



♠ DANGER

Danger to life due to fire or explosion when batteries are fully discharged!

A fire may occur due to incorrect charging of fully discharged batteries. This can result in death or serious injury.

- Make sure that the battery is not fully discharged before commissioning the system.
- Contact the battery manufacturer for further proceedings if the battery is fully discharged.



Danger to life due to burns caused by electric arcs through short-circuit currents!

Short-circuit currents in the battery can cause heat accumulation and electric arcs if the battery is short circuited or wrongly installed. Heat accumulation and electric arcs may result in lethal injuries due to burns.

- Disconnect the battery from all voltages sources prior to performing any work on the battery.
- Only use properly insulated tools to prevent accidental electric shock or short circuits during installation.
- Observe all safety information of the battery manufacturer.



♠ DANGER

Danger to life due to electric shock when touching live system components in case of a ground fault!

If a ground fault occurs, parts of the system may still be live. Touching live parts and cables may result in death or lethal injuries due to electric shock.

- Disconnect the product from voltage and energy sources and ensure it cannot be reconnected before working on the device.
- Only touch the cables of the PV modules on their insulation.
- Do not touch any parts of the substructure or frame of the PV array.
- Do not connect PV strings with ground faults to the product.



WARNING

Danger to life due to electric shock from destruction of the measuring device due to overvoltage!

Overvoltage can damage a measuring device and result in voltage being present in the enclosure of the measuring device. Touching the live enclosure of the measuring device results in death or lethal injuries due to electric shock.

Only use measuring devices with the measurement span higher than the DC input voltage range equal to or higher than the voltage rating of the product.



Risk of burns due to high temperature.

Some parts of the enclosure can become hot during operation.

During operation, do not touch any parts other than the enclosure lid of the product.



↑ CAUTION

Risk of injury due to weight of product.

Injuries may result if the product is lifted incorrectly or dropped while being transported or mounted.

- Transport and lift the product carefully. Take the weight of the product into account.
- Wear suitable personal protective equipment for all work on the product.

2.3 Symbols on the label



Beware of a danger zone!

This symbol indicates that the product must be additionally grounded if additional grounding or equipotential bonding is required at the installation site.



Beware of high voltage and operating current!

The inverter operates at high voltage and current. Work on the inverter must only be carried out by skilled and authorized electricians.



Beware of hot surfaces!

The inverter can get hot during operation. Avoid contact during operation.



WEEE designation

Do not dispose of the product together with the household waste but in accordance with the disposal regulations for electronic waste applicable at the installation site.



The product complies with the requirements of the applicable EU directives.



Certification mark

The product has been tested by TUV and got the quality certification mark.



RCM (Regulatory Compliance Mark)

The product complies with the requirements of the applicable Australian standards.



Capacitor discharge


Danger to life due to high voltages in the inverter. Do not touch live parts for at least 10 minutes after disconnection from the power sources.




Observe the documentation

Read and understand all documentation supplied with the product.

3 Eu Declaration of Conformity





4 EU Declaration of Conformity

Within the scope of the EU directives


Radio Equipment Directive 2014/53/EU
(L 153/62-106. May 22. 2014) (RED)



Restriction of the use of certain hazardous substances 2011/65/EU
(L 174/88, June 8, 2011) and 2015/863/EU (L 137/10, March 31,2015) (RoHS)


AISWEI Technology Co., Ltd. confirms herewith that the products described in this document are in compliance with the fundamental requirements and other relevant provisions of the above mentioned directives. The entire EU Declaration of Conformity can be found at www.solplanet.net.

5 Overview



Object	Description
1	Battery Connector Port
2	DC-Switch
3	PV Input
4	Ai-Dongle
5	Communication Ports
6	Diesel Generator Connector Port
7	AC Connector Port
8	EPS Load Connector Port
9	Additional Grounding Screw

6 Scope of Delivery



Object	Description	Type/Quantity					
Α	Inverter	1					
В	Mounting bracket	1					
С	Ai-Dongle	1					
	AC connector (black)	1					
D	Tubular terminal	5					
	Hex Key S=2.5	1					
	EPS Load connector (blue)	1					
E	Tubular terminal	5					
	Hex Key S=2.5	1					
	Diesel generator connector (red)	1					
F	Tubular terminal	5					
	Hex Key S=2.5	1					
G	DC connector	PV-C3F-S 2.5-6(+)-1386381 ASW05-12kH-T2-DG	2				
ď	DO COMINGCION	PV-C3M-S 2.5-6(-)-1386384 ASW08-15kH-T3-DG	3				
	Dattamiaanaatan	Socket: PV-KBT4-EVO ST/6I					
Н	Battery connector	Plug: PV-KST4-EVO ST/6I					
	Crimp contact (6mm²)	PV-BP4-EVO 2/6					

		PV-SP4-EVO 2/6	1	
1	Dattamyaannaatan	Socket: PV-KBT4-EVO ST/10II	1	
	Battery connector	Plug: PV-KST4-EVO ST/10II		
	O.:	PV-BP4-EVO 2/10		
	Crimp contact (10mm²)	PV-SP4-EVO 2/10	1	
J	Document	1		
K	Smart meter	1		
L	Fastener package	1		
М	Communication terminal package	1		



External CT connection and Smart Meter connection.

One E-Meter communication option is mandatory, when the inverter is operating in Self-Consumption mode, described in 16.2.1 and 16.2.2.

7 Solplanet App

7.1 Brief introduction


Solplanet App is an Android and iOS App which can establish communication connection to the inverter via the included communication device for remote and near-end initial setup and maintenance on the inverter.


7.2 Download and install

Scan the following QR code which directs to Google Playstore or Apple App Store, download and install the Solplanet App according to the prompt information.




8 Mounting Environment




















9 Dimensions





*ASW05-12kH-T2/T3 : 240.4mm ASW15kH-T3 : 245mm


10 Mounting


















11 Second Protective Grounding











12 AC Connection




























NO.	icon	Connector number	Line color
1		L1	brown
2		L2	black
3		L3	grey
4		N	blue
5		PE	yellow-green


13 EPS Load Connection






























14 Diesel Generator Connection




























15 DC Connection


TYPE 1


































16 Battery Connection





















17 Communication Setup

17.1 Communication connection












Object	Description	Termina	PIN definition							
Object			1	2	3	4	5	6	7	8
4	TCP/IP	RJ-45	TX+	TX-	RX+	Х	Х	RX-	Х	Х
6	BMS	RJ-45	Х	GND	Х	CANAH	CANAL	Х	х	Х
6	Monitor	RJ-45	RS485A	RS485B	GND	х	х	х	х	х


		Termin	PIN definition						
Object	Object Description	al	1	2	3	4	5	6	
А	DO2/DO1	4pin	Multifunction Relay		Multifunction Relay/Generator startup signal Relay		\		
			Α	В	Α	В			
В	\	Smart Meter \ (netv		(netwo	otection ork and rotection) vice				
			RS485A	RS485B				Negative	
			Ripp	le Control	Receiver Device		DRMS	Device	
С	DI*4/DRM0	6pin	DI_4	DI_3	DI_2	DI_1	REF GEN/0	COM LOAD/0 or GND	
	OT	Cu:	Current Transformer		Current Transformer L2			rent rmer L3	
D	CT	6pin	Red L1	Black	Red	.2 Black	Red	Black	
E*1	RS485	4pin	RS485A	RS485B	GND	/ black	Red	Diack	
F*1	RS485	4pin	RS485A	RS485B	GND	/			


^{*1} If E and F are connected to an inverter that supports only the parallel RJ45 interface, the RJ45 interface Pin1 is RS485A and Pin2 is RS485B













17.2 E-Meter communication

17.2.1 Current Transformer connection (optional)




17.2.2 Smart meter connection (Eastron SDM630-Modbus V2)




17.2.3 Smart meter connection(Eastron SDM630-Modbus V2)


The grid structure supported by the product is TN-S. For other grid types, please refer to 4.4.




17.2.4 Smart meter connection (CHINT DTSU666)





17.3 System Communication Connection: LAN Stick





17.3.1 Ai-Dongle connection























18 Contact

Please contact our Service Department if you have any technical questions about our products.

The following information is needed to provide necessary assistance:

- --Inverter model
- --Inverter serial number
- -- Photovoltaic module model
- -- Photovoltaic modules number and strings number connected to each MPPT
- --Fault code
- -- Installation location

EMEA

Service email: service.EMEA@solplanet.net

APAC

Service email: service.APAC@solplanet.net

LATAM

Service email: service.LATAM@solplanet.net

Aiswei Greater China

Service email: service.china@aiswei-tech.com

Hotline: +86 400 801 9996

Taiwan

Service email: service.taiwan@aiswei-tech.com

Hotline: +886 809089212

https://solplanet.net/contact-us



AISWEI Technology Co., Ltd. Web: www.solplanet.net

Add.: No. 18, Alley 600, Nanchezhan Road, Huangpu District, Shanghai, China